

Auto LED Flasher **WM FLL502KT**

L×W×H(mm): 30×30×39



Features

- Suitable for flasher light during car turning;
- Wide operating voltage, temperature range and long life;
- Standard terminals, usage and Replacement easily;
- With ticking sound.

Ordering Information

WM FLL502KT - 12	
1	2
1 Part number: WM FLL502KT	2 Rated Voltage(VDC): 12: 12V; 24: 24V

Technical Characteristics

Rated Voltage	12VDC, 24VDC
Operating Voltage	11VDC ~ 15VDC, 22VDC ~ 30VDC
Test Voltage	13VDC ± 0.2VDC, 26VDC ± 0.4VDC
Test Temperature	20°C ± 2°C
Switch Load	0.1W ~ 150W (0.02A ~ 20A)
Max Power	150W
Flashing Frequency	60 ~ 120 times per minute
Duty Ratio	30% ~ 70%
Operating Temperature	-40°C ~ +80°C
Life	400 working hours
Weight(Approx.)	30g

Layout (Bottom views, Unit: mm)

<p>Dimensions</p>	<p>Wiring diagram(Bottom views)</p>
--------------------------	--